

USER MANUAL

COMP-NOVA





COMPRESSOR PEDAL

Congratulations on your purchase of T-REX COMP-NOVA

Comp-Nova is a compressor pedal with a perfectly simple set of controls and pure, naturally compressed sound.

It "evens out" the irregularities in your signal by lowering high-input signals while boosting low-input signals, giving you smooth sustain without degrading the clarity and dynamics of the original sound.

COMPRESSION DONE RIGHT

If you've never used a compressor before, the effect can seem complicated at first. But it only takes an hour or so of experimenting and you'll discover a world of settings that add the subtle enhancement only a compressor can provide.

Place your Comp-Nova in the beginning or in the end of the pedal chain - it's all a matter of taste. For long sustain, the compressor should be placed after the distortion pedals.

CONTROLS

The **COMP knob** determines the compression amount. The more you turn it up, the more you compress your sound.

The **ATTACK knob** controls the sensitivity - how much of the signal will be compressed. Longer Attack times mean more natural signal before the compressor starts to work.

The **LEVEL knob** sets the overall volume. At max. level the signal is boosted approximately 3dB.

TECHNICAL SPECIFICATIONS

| | |
|------------------------------------|---|
| Input Impedance@1KHz | Higher than 1M Ohm |
| Output Impedance@1KHZ | Lower than 1K Ohm |
| Power supply | 9V DC (T-Rex FuelTank) |
| Minimum Power supply Voltage | 8V DC |
| Maximum Power supply Voltage | 12,5V DC |
| Current Draw @ 9V DC | 11 mA |
| Maximum Input signal Vp/p | 1,5Vp/p |
| Battery Type | 9 V battery 6F22 |
| Battery Life | 8 to 11 Hours |
| External connectors | Input Jack, Output Jack, 9V DC jack |
| Controls | On/Off, Level, Comp, Attack |
| Pedal size incl. knobs (W x H x D) | 100 x 55 x 120 mm 3,9 x 2,2 x 4,7 inch |
| Weight excl. battery and packaging | 0,310 kg / 10,9 oz |

T-REX WARRANTY CONDITIONS

T-Rex offers a 2-year warranty on all our products. In the unlikely event of a malfunction, please contact our technical support at info@t-rex-effects.com before sending us the product for repair. When the product has been sent to us at sender's cost, we will repair or replace your product and send it back to you - free of charge and usually within 3 weeks (shipping not included). The product needs to be accompanied by a copy of your receipt, serial number, return address, phone number, e-mail address and a brief explanation of the problem. Please note that we cannot replace a product until we have received it here in Denmark.

The warranty is lost if the product has been damaged by alteration, misuse, accident, or neglect; or if the product has been repaired or serviced by persons not authorized by T-Rex. Read more about warranty conditions at www.t-rex-effects.com.

ABOUT T-REX

Based in Vejle, Denmark, T-Rex Engineering makes classic and signature effects pedals for the world's best musicians. Our approach blends hi-tech innovation with old-world craftsmanship – always in the service of killer tone.

EU REGULATIONS • ENVIRONMENT PROTECTION

T-Rex accepts and follows the regulations and directives issued by the EU. We find these environment protecting regulations very good, and we are happy to follow them.



ISSUED IN VEJLE, 2002

Steen Meldgaard

Steen Meldgaard Laursen
Managing Director

Lars Dahl-Jørgensen

Lars Dahl-Jørgensen
Development Director

Sebastian Jensen

Sebastian Jensen
Production Director



T-Rex Engineering ApS
www.t-rex-effects.com