

HOTONE

SOUL PRESS

VOLUME/EXPRESSION/WAH-WAH PEDAL

Owner's Manual

THANK YOU FOR PURCHASING A HOTONE PRODUCT!

www.hotoneaudio.com

PRESS
SERIES PEDAL



SOUL PRESS

VOLUME/EXPRESSION/WAH-WAH PEDAL

- 1.INPUT: 1/4" mono audio jack, for connecting guitar.
- 2.MODE selector:
 - VOL—Volume mode, for use as volume pedal.
 - EXP—Expression mode, for connecting to another device with EXP control IN jack. EXP mode can work without power supply, if the pedal doesn't work, hit the footswitch and try again (without power, the lights will not appear to indicate if the pedal is switched on or off).
 - WAH—Wah mode, for use as a wah pedal.
- 3."DC IN": Plug in 9V DC adapter (center negative).

SOUL PRESS

VOLUME/EXPRESSION/WAH-WAH PEDAL



- 1.OUTPUT: 1/4" mono audio jack, for signal out or expression control out.
When used as an expression pedal, it needs a stereo cable with 1/4" stereo plugs at both ends of the cable.
- 2.BOTTOM VALUE:
Valid when in VOL and EXP mode, adjust the control range from 0%~100% to 50%~100%.
- 3.LEDs:
Indicates effects or bypass/off status, the pedal is working when LEDs are lit up.
- 4.Footswitch: Switch between effects and bypass/off status.

HOTONE

Soul Press is a Volume / Expression / Wah 3 in 1 pedal.

Features

- True bypass
- Extremely compact size
- Cool LED lights
- 3 in 1 pedal (Volume/Expression/Wah)
- Sound based on the original CryBaby* wah pedal
- Active volume mode for keeping lossless tone
- Adjustable control range (bottom value)
- 9V DC or 9V battery power supply

* CryBaby is a wah pedal model of Dunlop Manufacturing, Inc., the mentioned manufacturer and product names are trademarks or registered trademarks of their respective owners, the trademarks were used merely to identify the sound character of this product.

Specifications

Input Impedance (VOL Mode): 1M Ohms
Output Impedance (VOL Mode) : 100 Ohms
Current Consumption: Max 20mA
Dimensions: 138mm (D) x 62.5mm (W) x 51mm (H)
Weight: 340g

SOUL PRESS

VOLUME/EXPRESSION/WAH-WAH PEDAL